

Business Test and Tag Requirements

TABLE 4					
Indicative testing and inspection intervals for electrical equipment					
CAUTION: This page must be read in conjunction with AS/NZS3760 as a whole, and particularly 2.1					
Type of environment and/or equipment (a)	Interval between inspection and tests				
	Equipment Including Class I equipment, Class II equipment, cord sets, cord extension sets and EPODS (b)	Residual current devices (RCDs)			
		Push-button test		Operating time test	
		Portable (c)	Fixed (d)	Portable (e)	Fixed (f)
1. Factories, Workshops, places of work or repair, manufacturing, assembly, maintenance or fabrication	6 months	Daily, or before every use	6 months	12 months	6 months
2. Environment where the equipment or supply flexible cord is subject to flexing in normal use OR is open to abuse OR is in a hostile environment	12 months	3 months	6 months	12 months	6 months
3. Environment where the equipment or supply cord is NOT subject to flexing in normal use and is NOT open to abuse and is NOT in a hostile environment	5 years	3 months	6 months	2 years	5 years
4. Residential type areas of: hotels, residential institutions, motels, boarding houses, halls, hostels, accommodation houses and the like	2 years	6 months	6 months	2 years	2 years
5. Equipment used for commercial cleaning	6 months	Daily, or before every use	N/A	12 months	N/A
6. Hire equipment: Inspection	Prior to hire	Including push button test by hirer prior to hire		N/A	N/A
Test and tag	3 months	N/A		3 months	12 months
7. Repaired, serviced and second-hand equipment	After repair or service which could affect electrical safety, or on reintroduction to service, refer to AS/NZS 5762				